



## GO-01/02

This product specification is for preview purposes only and is subject to change without notice. The device is available in 2 versions:

**GO-01:** single modem, 2 external antennas

**GO-02:** double modem, 2 external antennas

Maximum load balancing capacity	950 Mbps
Phantom VPN encryption	180 Mbps
IPSec VPN encryption	60 Mbps
Maximum number of simultaneous WANs	5
Dimensions w x h x d	79mm x 140.7mm x 30mm (3.11in x 5.54in x 1.18in)
Weight	330g (11.64oz)
Operating temperature	5°C to 35°C (41°F to 95°F)
Humidity	5% to 85%
Power supply	USB-C 5V, 3A
(Model 1) Integrated cellular	1 CAT12
(Models 2) Integrated cellular	2 CAT12
Ethernet (WAN and/or LAN)	2 x 10/100/1000 Mbps RJ-45
Wi-Fi (WAN and/or LAN)	2.4GHz + 5GHz simultaneous dual-band
USB	2 x USB-C (self-charging, other device charging)
SIM card slot	2 x Micro
Battery power rating	10000mAh
Operating time	7 hours
LTE antenna connectors	2 x SMA female

Celerway's multi-WAN routers and M2M devices are powered by CelerwayOS, providing the best price per performance in their class. Priced to scale, our hardware solutions are ideal for large deployments in transportation, retail, and more.

## celerwayOS

Our lightweight and robust router software, built on open source and designed with mobile in mind. It continuously monitors traffic and network health against dozens of parameters and performs intelligent routing across multiple simultaneous WANs.

## phantom

A key component of CelerwayOS that enables:

---

Dynamic VPN load balancing

---

Seamless switching between multiple networks

---

Uninterrupted high-speed VPN and site-to-site communications

---

Ultra-flexible network topologies

---

On-premise or cloud-based operation on virtual machines or x86 hardware

## nimbus

Our remote administration system for deploying and managing devices running CelerwayOS:

---

User-friendly dashboard and comprehensive live reporting

---

Powerful features for mass deployment

---

Secure access with 2-factor authentication

---

Flexible notification and alerts system

---

Timely and worry-free firmware updates



At Celerway, we're on a mission to keep business ahead of the mobile curve.

The Celerway mobile-first platform enables customers to harness the power of multiple simultaneous wireless and wired connections to take their networks where they want them to be, thus expanding the reach of their SD-WAN or edge and branch networking solutions.

Based in Oslo, Norway, Celerway was founded in 2012 to bring the results of advanced research into the real world. Since then, our mobile-first CelerwayOS has been proven with customers worldwide by our OEM partners and our global network of distributors and resellers offering Celerway's range of wireless WAN routers in Europe, North America, Africa, and Asia.



## GO-01/02

This technical specification is for preview purposes only and is subject to change without notice. The device is available in 2 versions:

**GO-01:** single modem, 2 external antennas

**GO-02:** double modem, 2 external antennas

Wi-Fi module	MT7603 (2.4) + MT7612 (5) simultaneous
Wi-Fi protocol	b,g,n + a,b,g,n,ac
Wi-Fi theoretical data rate	300Mbps + 867Mbps
Frequency bands LTE-FDD	B1/B2/B3/B4/B5/B7/B8/B9/B12/B13/B14/B17/B18/B19/B20/B21/B25/B26/B28/B29/B30/B32/B66
Frequency bands LTE-TDD	B38/39/B40/B41
<b>GO-01 (1 x CAT12)</b>	
LTE theoretical data rate	DN: 600 Mbps, UP:150 Mbps
2 x CA	B1+3/5/18/19/20/26; B2+2/4/5/12/13/17/29/30/66; B3+3/5/7/8/19/20/28; B4+4 (CA_4C only)/5/12/13/17/29/30; B5+7/25/30/66; B7+7/20/28; B12+25;B12+30; B13+66; B19+21; B20+B32; B25+25,B25+26,B25+41; B29+30; B38+38 (CA_38C only); B39+39 (CA_39C only); B39+39; B39+41, B40+40 (CA_40C only); B41+41; B66+66 (CA_66C only)/12/29/30; B2+B14; B14+B30; B14+B66;
3 x CA	1A+3A+5A, 1A+3A+8A, 1A+3A+20A, 1A+3A+28A, 1A+5A+7A, 1A+7A+20A, 1A+7A+28A, 3A+3A+8A, 3A+7A+8A, 3A+7A+20A,3A+7A+28A, 1A+3C, 3A+7B, 3A+7C, 3C+5A, 3C+7A, 3C+20A, 5A+40C, 7B+28A, 7C+28A, 28A+40C, 40D + 1A+3A+5A, 1A+3A+8A, 1A+3A+20A, 1A+3A+28A, 1A+5A+7A, 1A+7A+20A, 1A+7A+28A, 3A+3A+8A, 3A+7A+8A, 3A+7A+20A,3A+7A+28A, 1A+3C, 3A+7B, 3A+7C, 3C+5A, 3C+7A, 3C+20A, 5A+40C, 7B+28A, 7C+28A, 28A+40C, 40D

GO-o2 (2 x CAT12)

LTE theoretical data rate	DN: 2 x 600 Mbps, UP: 2 x 150Mbps
2 x CA	<p>B1+3/5/18/19/20/26; B2+2/4/5/12/13/17/29/30/66;            B3+3/5/7/8/19/20/28;            B4+4 (CA_4C only)/5/12/13/17/29/30;            B5+7/25/30/66; B7+7/20/28; B12+25; B12+30; B13+66;            B19+21; B20+B32; B25+25, B25+26, B25+41; B29+30;            B38+38 (CA_38C only);            B39+39 (CA_39C only); B39+39; B39+41,            B40+40 (CA_40C only); B41+41;            B66+66 (CA_66C only)/12/29/30;            B2+B14; B14+B30; B14+B66;</p> <p>+</p> <p>B1+3/5/18/19/20/26; B2+2/4/5/12/13/17/29/30/66;            B3+3/5/7/8/19/20/28;            B4+4 (CA_4C only)/5/12/13/17/29/30;            B5+7/25/30/66; B7+7/20/28; B12+25; B12+30; B13+66;            B19+21; B20+B32; B25+25, B25+26, B25+41; B29+30;            B38+38 (CA_38C only);            B39+39 (CA_39C only); B39+39; B39+41,            B40+40 (CA_40C only); B41+41;            B66+66 (CA_66C only)/12/29/30;            B2+B14; B14+B30; B14+B66;</p>
3 x CA	<p>1A+3A+5A, 1A+3A+8A, 1A+3A+20A, 1A+3A+28A,            1A+5A+7A, 1A+7A+20A, 1A+7A+28A, 3A+3A+8A,            3A+7A+8A, 3A+7A+20A, 3A+7A+28A, 1A+3C,            3A+7B, 3A+7C, 3C+5A, 3C+7A, 3C+20A, 5A+40C,            7B+28A, 7C+28A, 28A+40C, 40D + 1A+3A+5A,            1A+3A+8A, 1A+3A+20A, 1A+3A+28A, 1A+5A+7A,            1A+7A+20A, 1A+7A+28A, 3A+3A+8A, 3A+7A+8A,            3A+7A+20A, 3A+7A+28A, 1A+3C, 3A+7B, 3A+7C,            3C+5A, 3C+7A, 3C+20A, 5A+40C, 7B+28A, 7C+28A,            28A+40C, 40D</p> <p>+</p> <p>1A+3A+5A, 1A+3A+8A, 1A+3A+20A, 1A+3A+28A,            1A+5A+7A, 1A+7A+20A, 1A+7A+28A, 3A+3A+8A,            3A+7A+8A, 3A+7A+20A, 3A+7A+28A, 1A+3C,            3A+7B, 3A+7C, 3C+5A, 3C+7A, 3C+20A, 5A+40C,            7B+28A, 7C+28A, 28A+40C, 40D + 1A+3A+5A,            1A+3A+8A, 1A+3A+20A, 1A+3A+28A, 1A+5A+7A,            1A+7A+20A, 1A+7A+28A, 3A+3A+8A, 3A+7A+8A,            3A+7A+20A, 3A+7A+28A, 1A+3C, 3A+7B, 3A+7C,            3C+5A, 3C+7A, 3C+20A, 5A+40C, 7B+28A, 7C+28A,            28A+40C, 40D</p>